

Washer extractor Metos FX135

Freestanding washer with stainless steel top panel and anthracite grey front and side panel. Large door opening Ø 410 mm for easy loading and unloading

- stainless steel Ø 620 mm drum, volume 135 litres
- wash speed 49 rpm
- extraction: 1075 rpm
- X control - easy to use microprocessor with 15 pre-set programs
- spin 400 G-factor
- easy access to all vital parts from the front
- patented soap hopper
- large drain valve (Ø76 mm)
- frequency controlled motor
- PowerWash® perforated lifting ribs more mechanical action, lower water consumption
- measurement of unbalance by means of frequency inverter
- SuperEco washing programmes
- significantly reduces water and electricity consumption

Accessories:

- plinth 135 mm
- plinth 200 mm



Washer extractor Metos FX135

Product capacity	14 kg
Item width mm	795
Item depth mm	945
Item height mm	1225
Package volume	1.106
Unit of volume	m3
Package volume	1.106 m3
Package length	83.5
Package width	98.5
Package height	134.5
Package unit of dimension	cm
Package dimensions (LxWxH)	83.5x98.5x134.5 cm
Net weight	255
Net weight	255 kg
Gross weight	275
Package weight	275 kg
Unit of weight	kg
Connection power kW	12
Fuse Size A	25
Connection voltage V	400
Number of phases	3NPE
Frequency Hz	50
Protection rating (IP)	44
Type of electrical connection	Semifixed
Electrical conn. inlet	Top;Behind
Electrical conn. height mm	1120
Remarks (electrical)	Heating power 12kW
Cold water diam.	3/4"
Cold water flow l/min	20

Washer extractor Metos FX135

Cold water min pressure kPa	100
Cold water max pressure kPa	800
Cold water conn. inlet	Top;Behind
Cold water conn. height mm	1030
Remarks (cold water)	water consumption 7,2 l/kg
Hot water diam.	3/4"
Hot water flow l/min	20
Hot water conn. inlet	Top;Behind
Drain conn. inlet	Behind;Right
Drain conn. height mm	88
Floor drain needed	Yes
Sound level dB	65
Type	electric
Operation type	electronical
Hinge location	right
Drum material	stainless steel
Programmability	ready programs
Amount of programs	15
Insulation	insulated
Drain pump	No